



| Material | Capacity (lb) | A       | В       | C       | D       | E       | F       |
|----------|---------------|---------|---------|---------|---------|---------|---------|
| (AL*)    | 10            | 1915.87 | 1706.49 | 1369.65 | 4811.88 | 5642.46 | 1020.12 |

## $\sigma_{ m max}$ Table

| Material     | Static Load<br>(=60% Y.S.) | Fatigue<br>(Non Reversing<br>Loads) | Fatigue<br>(Full Reversing<br>Loads) |  |
|--------------|----------------------------|-------------------------------------|--------------------------------------|--|
| 2024-T4/T351 | 28,000                     | 18,000                              | 15,000                               |  |

<sup>\*</sup>Value is 75% of Fatigue Strength based on 10-20 x 106 cycles and allow for factors that influence Fatigue such as surface finish, stress concentrations, corrosion, temperature and other variables for the production of the transducer, for infinite Fatigue Life (100 x 106) use 75% of values shown.

## **Deflection & Natural Frequency**

| Material | Capacity (lb) | Deflection<br>(in.) | Natural<br>Frequency<br>(Hz) | β      |
|----------|---------------|---------------------|------------------------------|--------|
| (AL*)    | 10            | 0.004               | 1,700                        | 0.0080 |

<sup>\*</sup>FN results are based on calculation of deflection & weight scene on Sensor arm.

## Natural Frequency & Frequency Response Equation's:

Natural Frequency (FN) = 
$$3.13 \sqrt{\frac{1}{\frac{\beta}{Capacity}} \bullet Deflection}}$$
 (Hz)

This documentation was generated and completed to the best ability of FUTEK's Engineering Team using FEA Analysis, Empirical data and Multiple Testing Simulations. The information and recommendations on this document are presented in good faith and believed to be correct however, FUTEK Advanced Sensor Technology makes no representations or warranties as to the completeness or accuracy of the information.



## Model #LSM200 (L2341) Series Doc#: EL1050



Frequency Response with load (FR) = 
$$3.13 \sqrt{\frac{1}{\frac{\beta + AppliedLoad}{Capacity}}} \bullet Deflection$$
 (Hz)

\*Where eta values are obtained by Futek Engineers

This documentation was generated and completed to the best ability of FUTEK's Engineering Team using FEA Analysis, Empirical data and Multiple Testing Simulations. The information and recommendations on this document are presented in good faith and believed to be correct however, FUTEK Advanced Sensor Technology makes no representations or warranties as to the completeness or accuracy of the information.

