


## **Extraneous Load Factors**

**Equation:**  $\sigma_{\text{max}} \ge (A)Fx + (B)Fy + (C)Fz + (D)Mx + (E)My + (F)Mz$ 



Material: 17-4 P.H. Stainless Steel

Model #	Capacity (lb)	A	В	C	D	E	F
LSB352	500	91.00	83.15	76.02	62.37	52.11	46.70
LODOOZ	1,000	73.54	82.74	50.66	63.88	49.88	38.89

## $\sigma_{\rm max}$ Table

Material	Static Load (=60% Y.S.)	Fatigue (Non Reversing Loads)	Fatigue (Full Reversing Loads)
17-4PH S.S	87,000	78,000	62,000*

<sup>\*</sup>Value is 75% of Fatigue Strength based on  $10\text{-}20 \times 10^6$  cycles and allow for factors that influence Fatigue such as surface finish, stress concentrations, corrosion, temperature and other variables for the production of the transducer, for infinite Fatigue Life ( $100 \times 10^6$ ) use 75% of values shown.

## **Deflection & Natural Frequency**

Model #	Capacity (lb)	Deflection (in.)	Natural Frequency (Hz)	β
LSB352	500	0.006	340	0.7000
LODOOZ	1,000	0.010	1,200	0.7000


## Natural Frequency & Frequency Response Equation's:

Natural Frequency (FN) = 
$$3.13 \sqrt{\frac{1}{\frac{\beta}{Capacity}} \bullet Deflection}}$$
 (Hz)

Frequency Response with load (FR) = 
$$3.13 \sqrt{\frac{1}{\frac{\beta + AppliedLoad}{Capacity}} \bullet Deflection}}$$
 (Hz)

\*Where eta values are obtained by Futek Engineers

This documentation was generated and completed to the best ability of FUTEK's Engineering Team using FEA Analysis, Empirical data and Multiple Testing Simulations. The information and recommendations on this document are presented in good faith and believed to be correct however, FUTEK Advanced Sensor Technology makes no representations or warranties as to the completeness or accuracy of the information.



Page 1 of 2

Model #LSB352 (L2372) Series



This documentation was generated and completed to the best ability of FUTEK's Engineering Team using FEA Analysis, Empirical data and Multiple Testing Simulations. The information and recommendations on this document are presented in good faith and believed to be correct however, FUTEK Advanced Sensor Technology makes no representations or warranties as to the completeness or accuracy of the information.

Doc#: EL1045